
ADC[®] Diagnostix[™] 2100 Fingertip Pulse Oximeter

Directions
for Use



ADC® Fingertip Pulse Oximeter

Thank you for purchasing an ADC Diagnostix™ Brand Fingertip Pulse Oximeter. We're proud of the care and quality that goes into the manufacture of every product that bears our name. With proper care and maintenance your Diagnostix™ Fingertip Pulse Oximeter will provide many years of dependable service.

Device Description and Intended Use

This device is intended for medical diagnostic purposes only. It is used to indirectly measure the functional oxygen saturation (SpO₂) of an adult or pediatric patient's blood. It is intended for use on fingers with a thickness of 8mm to 20mm (.31" to .79"). This is the distance between the fingernail (top), and the finger pad (bottom). Functional oxygen saturation refers to the ratio of oxyhemoglobin to all hemoglobin that is capable of carrying oxygen. This oximeter is not intended for continuous monitoring. The Pulse Oximeter requires no routine calibration or maintenance other than replacement of batteries.

Pulse oximetry combines the principles of optical plethysmography and spectrophotometry to determine arterial oxygen saturation values. Optical plethysmography uses light absorbance technology to reproduce waveforms produced by pulsating blood. Spectrophotometry uses various wavelengths of light to perform quantitative measurements about light absorption. Photoelectric Oxyhemoglobin Inspection Technology is combined with Capacity Pulse Scanning and Recording Technology, so that two beams of different wavelengths of light (660nm glow and 940nm near infrared light) can be focused onto the human nail tip through a finger-tip sensor. These two LED's are chosen because the light absorption varies with the oxygen concentration of hemoglobin in these frequencies. The pulse amplitudes of the red and near infrared signals are detected using photoelectric sensors and run through a microprocessor which converts the readings to numerical values.

Contraindications:

- The patient suffers from significant levels of dysfunctional hemoglobins (such as carboxyhemoglobin or methemoglobin).
- Intravascular dyes such as indocyanine green or methylene blue have been injected into the patient.
- Used in the presence of high ambient light (ie, direct sunlight). Shield the sensor area with a surgical towel if necessary.
- There is excessive patient movement.
- The patient experiences venous pulsations.
- The patient has hypotension, severe vasoconstriction, severe anemia, or hypothermia.
- The patient is in cardiac arrest or is in shock.
- Patients have fingernail polish or false fingernails as they may cause inaccurate SpO₂ readings.

Symbol Definitions

Symbol	Definition
	Important Warning/Caution
	Not made with natural rubber latex
	Equipment type is BF
% SpO ₂	Hemoglobin Saturation
	Heart Rate (BPM)
	Low Power Indication
	Not for Continuous Monitoring


Symbol	Definition
	Follow instructions for use
	Authorized European Representative Information
	Manufacturer's Information
	Serial Number
	Recyclable
	RX Only

General Warnings

A warning statement in this manual identifies a condition or practice which, if not corrected or discontinued immediately, could lead to patient injury, illness, or death.

-  **WARNING:** Before use, carefully read the manual.
-  **WARNING:** Do not use the pulse oximeter in an MRI or CT environment.
-  **WARNING:** The operation of Pulse Oximeter may be affected by the use of an electrosurgical unit (ESU).
-  **WARNING:** Federal law restricts this device to sale by or on the order of a physician or licensed healthcare practitioner.
-  **WARNING:** The pulse oximeter is intended only as an adjunct in patient assessment. It must be used in conjunction with other methods of assessing clinical signs and symptoms.
-  **WARNING:** Follow local ordinances and recycling instructions regarding disposal or recycling of the device and device components, including batteries.
-  **WARNING:** This product may contain a chemical known to the state of California to cause cancer, birth defects, or other reproductive harm.
-  **CAUTION: Do not use the pulse oximeter in an explosive atmosphere.**
-  **CAUTION:** SpO₂ and pulse rate data is displayed for informational purposes only and does not constitute a diagnosis or medical advice of any kind. Only a qualified healthcare professional should interpret the data obtained on this device.
-  **CAUTION:** Check the pulse oximeter sensor application site frequently to determine the positioning of the sensor and circulation and skin sensitivity of the patient.
-  **CAUTION:** The pulse oximeter is not for continuous monitoring.
-  **CAUTION:** Prolonged use or the patient's condition may require changing the sensor site periodically. Change sensor site and check skin integrity, circulatory status, and correct alignment at least every 4 hours.
-  **CAUTION:** Inaccurate measurements may be caused by autoclaving, ethylene oxide sterilizing, or immersing the sensors in liquid.
-  **CAUTION:** The device should not be used on an extremity with a blood pressure cuff, arterial catheter, or intravascular line.

Brief Description of Front Panel




Included Pulse Oximeter Accessories

- One (1) lanyard
- Two (2) AAA batteries
- One (1) user manual
- One(1) rubberized bumper

Battery Installation


1. Remove battery compartment cover by depressing button on battery cover top, then slide cover in the direction of the arrow, then tilt upward on hinge.
2. Insert two AAA batteries into battery compartment being sure to observe the correct polarities.
3. Replace the battery cover by reversing step 1. (Figure 1)



Note: Be sure to observe correct battery polarity. Failure to do so might damage the device. If device will not be used for an extended period of time, remove batteries. Replace batteries when low battery symbol appears on display. Always replace BOTH batteries at the same time

Operating Instructions

1. Be sure to insert two AAA batteries before attempting to operate.
2. Clean inside surface of oximeter and patient's finger with isopropyl alcohol before use.
3. Squeeze the end opposite the power switch between the thumb and forefinger in order to open the device. (there is a textured surface on the battery cover side to facilitate grip) (Figure 2)
4. Insert patient's finger, nail side up into the device. (be sure to fully insert the patient's finger so that the sensors are completely covered by the finger.) Index or middle finger is recommended.
5. Release the device allowing it to clamp down on the patient's finger.
6. Press the power switch on the front (top) panel to activate.
7. Have patient keep still for optimal accuracy.
8. Depending upon environmental and patient conditions, the device will begin to display readings in about 4 seconds.
9. Note readings on the display.
10. Remove the patient's finger from the device by squeezing between forefinger and thumb as indicated in Figure 2.
11. The display will indicate finger out.
12. The unit will power off approximately 10 seconds after the patient's finger is removed from the device.



Changing Oximeter Display Mode


There are six different display modes. The display modes alter the orientation of the display to facilitate reading by the observer. Horizontal modes display the pulse wave form along with SPO2 and pulse rate while vertical modes display a pulse rate bar graph along with the SPO2 and pulse rate readings.

To alter the display mode:


1. After the unit is powered on each brief press of the power switch will cycle through to the next display mode in the sequence shown.

Note: the default setting is display mode 1.

Display Mode Cycle




Normal Horizontal
Wave Display
(Default Setting)
No Pulse Tone
Alarm Tone Active




Normal Horizontal
Wire Display
(2nd click)
Pulse Tone Active
Alarm Tone Active




Normal Horizontal
(3rd click)
Pulse Tone Active
Alarm Tone Active



Handstand Horizontal
(4th click)
Pulse Tone Active
Alarm Tone Active



Normal Vertical
(5th click)
Pulse Tone Active
Alarm Tone Active



Handstand Vertical
(6th click)
Pulse Tone Active
Alarm Tone Active

Alarm

On models equipped with an alarm, the alarm condition will appear when:

SPO2 < 90% / PR <60 or >100bpm

If the unit is in display mode 1 (silent mode), the parameter (SPO or PR) flashes and an audible beep is heard if it exceeds the alarm condition. If the unit is in display modes 2-6 (audible mode), the unit will beep during measurement and will signal and alarm condition with both visual and audible alerts.

Note: The alarm can be deactivated for 30 seconds by pressing the power button once.

Note: This device is not intended for continuous patient monitoring. Alarm sounds are for reference purposes only.

Changing the Display Brightness (10 adjustable brightness settings)

To change the brightness setting:

1. After the unit is powered on, hold and depress the power switch. It will cycle through from BR4 up to BR10, then start back at BR1.

Note: The default setting is level 4 (BR4).

Lanyard Attachment

1. Thread thinner end of the lanyard through the hanging hole at the rear end of the device.
 2. Thread thicker end of the lanyard through the threaded end before pulling it tightly.
-

Care and Maintenance

1. Replace the batteries promptly when low voltage indicator appears.
2. Clean surface of the fingertip and oximeter with isopropyl alcohol before it is used in diagnosis for patients.
3. Remove the batteries if unit will not be operated for extended period of time.
4. It is best to store this product in a place where ambient temperature is -10°C -40°C(14°F -104°F) and humidity is 10%-80%.
5. It is recommended that the product should be kept in a dry environment at all times.
6. Please follow local ordinances when disposing of batteries.

Cleaning the Pulse Oximeter

Clean the rubber touching the finger inside of the Oximeter with a soft dampened cloth with 70% isopropyl alcohol, and clean the test finger using alcohol before and after each test.

Note: Do not pour or spray any liquids onto the Oximeter, and do not allow any liquids to enter any openings in the device. Allow the Oximeter to dry thoroughly before reusing.

Troubleshooting Possible Problems		
Problem	Possible Reason	Solution
SpO2% or pulse rate do not display normally.	<ol style="list-style-type: none">1. Finger is not inserted correctly.2. Patient SpO2 value is too low to be measured.	<ol style="list-style-type: none">1. Retry inserting the finger.2. There is excessive illumination.3. Measure more times. If you determine the product is working correctly, see your healthcare provider for an exact diagnosis.
SpO2% or pulse rate is shown unstably.	<ol style="list-style-type: none">1. Finger might not be inserted deep enough.2. Excessive patient movement.	<ol style="list-style-type: none">1. Retry inserting the finger.2. Sit calmly and retry.
The monitor cannot be powered on.	<ol style="list-style-type: none">1. No battery or low battery power.2. Battery not installed correctly.3. The monitor may be damaged.	<ol style="list-style-type: none">1. Replace battery.2. Remove and reinstall battery.3. Contact customer service center.
Indication is suddenly off.	<ol style="list-style-type: none">1. The Oximeter is automatically powered off, when no signal was detected after 8 seconds.2. The battery power is too low to operate.	<ol style="list-style-type: none">1. Normal.2. Replace batteries.
"Err 3" or "Err 4"	<ol style="list-style-type: none">1. ERR 3 means the red emission LED is damaged.2. Err 4 means the infra-red emission LED is damaged.	<ol style="list-style-type: none">1. Check the red emission LED.2. Check the infra-red emission LED.3. Return to Service Center
"Err 6"	Err 6 means crystal damage.	<ol style="list-style-type: none">1. Return to Service Center
"Err 7"	Err 7 means all the emission LED or reception diode is damaged.	<ol style="list-style-type: none">1. Return to Service Center

**Guidance and Manufacturer's Declaration
Electromagnetic Emissions**

Guidance and Manufacturer's declaration - electromagnetic environment specified below.
The customer or the user of the PULSE OXIMETER should assure that it is used in such an environment.

Emission Test	Compliance Level	Electronic Environment Guidance
RF Emissions CISPR11	Group 1	The PULSE OXIMETER uses very low RF energy only and is not likely to cause interference to nearby electronic equipment.
RF Emissions CISPR11	Class B	The PULSE OXIMETER is suitable for use in all establishments, including domestic and those directly connected to the public low-voltage power supply which powers buildings used for domestic purposes.
Harmonic emissions IEC 61000-3-2	Not applicable	
Voltage fluctuations/ Flicker emissions IEC 61000-3-2	Not applicable	

**Guidance and Manufacturer's Declaration - Electromagnetic Immunity
For all Equipment and Systems**

Guidance and Manufacturer's declaration - electromagnetic environment specified below.
The customer or the user of the PULSE OXIMETER should assure that it is used in such an environment.

Immunity Test	IEC 60601 Test Level	Compliance Level	Electronic Environment Guidance
Electrostatic Discharge (ESD) IEC 61000-4-2	+/- kV contact +/- 8kV air	+/- kV Contact +/- 8kV air	Floors should be wood, concrete, or ceramic tile. If floor is covered with synthetic material, the relative humidity should be at least 30%.
Power Frequency (50/60 Hz) Magnetic Field IEC 61000-4-8	3A/m	3A/m	Power frequency magnetic fields should be at levels characteristic of a typical location in a typical commercial or hospital environment.

**Guidance and Manufacturer's Declaration - Electromagnetic Immunity
For all Equipment and Systems that are not Life-Supporting**

Guidance and Manufacturer's declaration - electromagnetic environment specified below.
The customer or the user of the PULSE OXIMETER should assure that it is used in such an environment.

Immunity Test	IEC 60601 Test Level	Compliance Level	Electronic Environment Guidance
Radiated RF IEC 61000-4-3	3 V/m 80 MHz to 2.5 GHz	3 V/m	<p>Portable and mobile RF communications equipment should not be used close to any part of the Pulse Oximeter, including cables. The recommended separation distance should be calculated from the equation applicable to the frequency of the transmitter.</p> <p>Recommended separation distance 80MHz to 800MHz 800MHz to 2.5GHz</p> <p>Where P is maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer and (d) is the recommended separation distance in meters (m).</p> <p>Where P is the maximum output power rating of the transmitter in watts (W) according to the transmitter manufacturer and d is the recommended separation distance in meters (m).</p> <p>Field strengths from fixed RF transmitters, as determined by an electromagnetic site survey, should be less than the compliance level in each frequency range.</p>

NOTE 1: At 80MHz and 800MHz, the higher frequency range applies.

NOTE 2: These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection structures, objects and people.

A. Field strengths from fixed transmitters, such as base stations for radio, (cellular/cordless) telephones, and land mobile radios, amateur radio, AM/FM radio, and TV broadcasts cannot be predicted theoretically with accuracy. To assess the electromagnetic environment due to fixed RF transmitters, an electromagnetic site survey should be considered. If measured field strength in the location in which the Pulse Oximeter should be observed to verify normal operation. If abnormal performance is observed, additional measurements may be necessary, such as reorienting the location of the Pulse Oximeter.

B. Over the frequency range 150kHz to 80MHz, field strengths should be less than 3V/m.

**Recommended Separation Distance Between Portable and Mobile RF communication equipment
and the Equipment or Systems
For all equipment and Systems that are not Life-Supporting
Recommended separation distances between portable and mobile RF communications equipment
and Pulse Oximeter**

The Pulse Oximeter is intended for use in electromagnetic environment in which radiated RF disturbances are controlled. The customer or the user of the Pulse Oximeter can help prevent electromagnetic interference by maintaining a minimum distance between portable and recommended below, according to the maximum output power of the communications equipment.

Rated maximum Output power of transmitter (W)	Separation distance according to frequency of transmitter (m)	
	80 MHz to 800 MHz	800 MHz to 2.5 GHz
0.01	0.1167	0.2334
0.1	0.3689	0.7378
1	1.1667	2.3334
10	3.6893	7.3786
100	11.6667	23.3334

For transmitters rated at a maximum output power not listed above, the recommended separation distance (d) in meters (m) can be estimated using the equation applicable to the frequency of the transmitter, where (p) is the maximum output power rating of the transmitter in watts (w) according to the transmitter manufacturer.

NOTE 1: At 80 MHz and 800 MHz, the separation distance for the higher frequency range applies.

NOTE 2: These guidelines may not apply in all situations. Electromagnetic propagation is affected by absorption and reflection from structures, objects, and people.

Technical Specifications

Display Type:	OLED Display
SPO2 display range:	0-100%
PR Display Range:	30-235 BPM
PR Display Mode:	Bargraph
Data Update Time:	< 15 s

LED Wavelengths

Red:	660nm
Infrared:	940nm

Measurement range:

SPO2:	70-99% - 100% $\pm 3\%$; s 70% no definition
Pulse Rate:	30-235 BPM, ± 2 bpm during the pulse rate range of 30-99 bpm and 2% during the pulse rate range of 100-235 bpm.

Accuracy:	$\pm 2\%$ on the stage of 80%-99%; $\pm 3\%$ on the stage of 70%-80%;
-----------	--

Accuracy:	± 2 BPM or $\pm 2\%$ (larger)
Pulse Intensity:	Bargraph Indicator
Power Requirements:	Two AAA alkaline Batteries
Power consumption:	Less than 40mA

Low power indication:

Battery Life:	(2) "AAA" 1.5V, 600mAh alkaline batteries. Can operate as long as 30 hours (continuous).
---------------	---

Dimension:

Length:	2.3" (58mm)
Width:	1.3" (32mm)
Height:	1.3" (34mm)
Weight:	1.8oz. (50g) (including two AAA batteries)

Environment:

Operation Temperature:	41°F - 104°F (5°C - 40°C)
Storage Temperature:	14°F - 104°F (-10°C - 40°C)
Relative Humidity:	15%-80% in operation / 10%-80% in storage

Finger Range:	8mm-20mm (.31"-.79")
---------------	----------------------

Warranty

American Diagnostic Corporation (ADC®) warrants its products against defects in materials and workmanship under normal use and service as follows:

1. Warranty service extends to the original retail purchaser only and commences with the date of delivery.
2. Your Pulse Oximeter is warranted for two (2) years from date of purchase (all parts).

What is Covered: Replacement of parts, and labor.

What is Not Covered: Transportation charges to and from ADC®. Damages caused by abuse, misuse, accident, or negligence. Incidental, special, or consequential damages. Some states do not allow the exclusion or limitation of incidental, special, or consequential damages, so this limitation may not apply to you.

To Obtain Warranty Service: Send item(s) postage paid to ADC®, Attn: Repair Dept., 55 Commerce Dr., Hauppauge, NY 11788. Please include your name and address, phone no., proof of purchase, and a brief note explaining the problem.

Implied Warranty: Any implied warranty shall be limited in duration to the terms of this warranty and in no case beyond the original selling price (except where prohibited by law). This warranty gives you specific legal rights and you may have other rights which vary from state to state.

To register your product visit us at
www.adctoday.com/register

FOR QUESTIONS, COMMENTS,
OR SUGGESTIONS CALL TOLL FREE:

1-800-ADC-2670

OR VISIT

www.adctoday.com/feedback

This manual is available online in a variety of
languages, follow the links for language options.

www.adctoday.com/care



**Beijing Choice
Electronic Technology Co., Ltd.**
Room 4104, No. A12 Yuquan Road
Haidian District, 100143
Beijing, P.R. China



Shanghai International
Holding Corp. GmbH (Europe)
EiffestraBe 80, 20537
Hamburg, GERMANY

Dist. by: ADC®
55 Commerce Drive
Hauppauge, NY 11788

Inspected in the U.S.A.
Made in China
tel: 631-273-9600
1-800-232-2670
fax: 631-273-9659
www.adctoday.com

